

Hewlett Packard DL380 G8

- BIOS SATA AHCI, Legacy DVD-ROM.
- , , F6 acpi=off, .
- BIOS "-1":

1. ;
2. "-1" 1, 4, ;
3. BIOS F9;
4. Advanced Options;
5. Advanced System ROM Options;
6. Power-On Logo;
7. Disabled;
8. .

- RAID-:

1. hpsa.ko USB-flash .
2. .
3. (Ctrl+Alt+F2), USB-flash hpsa.ko :
dmesg
USB-flash (sda,sdb) (sda1,sdb1)

```
mkdir 1
mount -t vfat /dev/< > 1
: flash- ntfs( ntfs-3g -t vfat) ext( -t vfat)
```

```
cp /1/hpsa.ko /lib/modules/2.6.34-3-generic/kernel/drivers/scsi/
depmod -a
umount 1
```

flash-

modprobe hpsa

dmesg

, RAID- , .

4. (Alt+F5) , .
5. (Ctrl+Alt+F2), USB-flash hpsa.ko :

```
mount -t vfat /dev/< > 1
cp /1/hpsa.ko /target/lib/modules/2.6.34-3-generic/kernel/drivers/scsi/
mount proc -t proc /target/proc
chroot target
depmod -a
update-initramfs -u -t
exit
umount /target/proc
umount 1
```

6. (Alt+F5) .

2: [hpsa-3.1.0.tgz](#)

RAID- [hpsa.tgz](#)

- .

```
/lib/modules/2.6.34-3-generic/kernel/drivers/net :
mv bnx2.ko bnx2.ko.orig
mv bnx2x.ko bnx2x.ko.orig
mv cnic.ko cnic.ko.orig
```

```
/lib/modules/2.6.34-3-generic/kernel/drivers/net 644 root:root :
depmod -a
P.S. .
NetXtreme
NetXtremeII
NetXtreme, .
:
```

dpkg -i tg3-ossn-1.2_3.124c-1_amd64_specific.deb

[tg3-ossn-1.2_3.124c-1_amd64_specific.deb](#)

2: [NX.tgz](#)

NetXtreme II [NetXtreme2.tgz](#)

[NXII.tgz](#)

- HP 81E 8 Gb 1-port PCIe Fibre Channel Host Bus Adapter 10 Gb Single Port Ethernet x8 PCIe (LC) QLE 3240-SR [drivers_signed.tgz](#)
HP81 [hp-be2net-4.2.389.0-2.src.rpm.tgz](#)
Qlogic [qlcnlc-5.2.46.1-QLogic.tgz](#)